

Alarm Control Panels



LK-1002



LK-1004



LK-1006



LK-1008

- LK-1002 : 2 burglary zones (NC loop)
- LK-1004 : 4 burglary zones (NC loop)
- LK-1006 : 6 burglary zones (NC loop)
- LK-1008 : 8 burglary zones (NC loop)

Microprocessor controlled.

With one 24 hours emergency zone (NO loop)

Each zone supervised by end-of-line resistors and fast-response time

Individual By-pass switches and LED zone status indicators
Alarm memory for each zone, Battery recharge circuit, and optional remote control

Selectable options: Entry and Exit delay time

Siren alarm cut-off time

External siren wiring broken detection

Audible arm / disarm indication

Door chime

System outputs: one timing /latching relay (dry contact)

one timing alarm output 12VDC/1.0A

one ARM LED terminal output

one Auxiliary power output 12VDC/0.5A

Built-in transformer (18VA) and sounder

Dimensions: 213W x 300L x 70D mm