







REMOTE CONTROL SWITCH (580m)



- ◆ Power source : Receiver : DC 12V
Transmitter : DC 12V(A23) battery
- ◆ Effective distance : more than 580m (1900ft), line of sight.
- ◆ Frequency : 380 MHz(RF)
- ◆ Code combination : 10-bit DIP switch
- ◆ Mode selection : pulse or ON/OFF
- ◆ Relay contact : 5A/125VAC
- ◆ Dimension : Receiver : 48^W x 87^L x 23^D mm
Transmitter : 37^W x 70^L x 15^D mm

RC Mode	 1  2	Press button 1 or 2, the RELAY will be turned on until the button is released.
RM Mode	 1  2	Press button 1 or 2, the RELAY will be turned on and stay on for approximately 1 second.
R2 Mode	 1	Press button 1, the RELAY will be turned on.
	 2	Press button 2, the RELAY will be turned off.