

Wireless Autodialer

LK-119

- ✓ Home Care
- ✓ In an Emergency
- ✓ Robbery Prevention
- ✓ Retail-counter Safety

- ▶ Easy installation.
One push-button triggers eight emergency calls.
- ▶ Plays recorded message automatically. Keeps families, neighbors or the police informed.
- ▶ Designed and manufactured in Taiwan.



LK-119 Control Unit



Pendant Remote

Hand-held Remote



Get the World Patent

Taiwan Patent Number: M539131
Japan Patent Number: 3210037
China Patent Number: 201720424792.4

LK-119 *Call Help Dialer*

Wireless Autodialer



System Features & Functions:

The wireless Autodialer LK-119 comprises a system control unit and a wireless panic button which can be integrated into your daily life easily. All you have to do to get help is to push either the buttons on system control unit or the wireless panic button. In case of an emergency or crisis situation at home or shop.

The wireless Autodialer LK-119 features exclusive integrated designed to use with up to 15 units of wireless panic buttons to expand the system protection. The Autodialer automatically calls up to 8 specific phone numbers upon alarm activation, plays pre-recorded 20 seconds alarm notification voice message and allows call recipients to respond as necessary.

Specifications:

- Operating frequency: 395MHz / 318MHz / 433.92MHz
- RF reception range (for LK-119 control unit): up to 100m in a free space without interference.
- Telephone system: DTMF (Tone) dialing on PSTN.
- Phone number length: 25 digits max.
- Voice message duration: 20 seconds
- Number of phone numbers: 8 (landline or cellphone)
- Numbers of during attempts: 2~5 cycles.
- Power adaptor: DC12V / 1A
- Hand-held remote operating power: 12V/23A Alkaline Battery
- Pendant remote operating power: 12V/27A Alkaline Battery
- Operating temperature: -10°C ~ +50°C
- Dimensions: 210 (W) x 125 (H) x 34 (D) mm

Get the World Patent

- Taiwan Patent Number: M539131
- Japan Patent Number: 3210037
- China Patent Number: 201720424792.4

Standard Kit Package:

- | | |
|----------------------------|-----|
| 1. LK-119 Control unit | x 1 |
| 2. Power Adapter | x 1 |
| 3. Hand-held Remote | x 1 |
| 4. Pendant Remote | x 1 |
| 5. Telephone Split Adapter | x 1 |
| 6. Key | x 2 |